



NOTES.

1. Match Motor Flange: $\phi 50$
2. Output shaft have keyway, without keyway is optional.
3. Bushing is supplied to input bore $\phi 6, \phi 6.35, \phi 8, \phi 9, \phi 10, \phi 11$ or $\phi 12$.
4. $\phi C = \phi 11$ or $\phi 14$.

MODEL	段數 (Stage)	減速比 (Ratio)	背隙 (Arcmin)	匹配馬達出軸直徑&長度
PA050-C0038B1430	單段	3	8	14 & 30
PA050-C0048B1430	單段	4	8	14 & 30
PA050-C0058B1430	單段	5	8	14 & 30
PA050-C0078B1430	單段	7	8	14 & 30
PA050-C0108B1430	單段	10	8	14 & 30

Ration Application	3,4,5,7,10
Power Application	100W ~ 200W

DELTA 台達電子工業股份有限公司
DELTA ELECTRONICS, INC.

THESE DRAWINGS AND SPECIFICATIONS ARE THE PROPERTY OF DELTA ELECTRONICS, INC. AND SHALL NOT BE REPRODUCED OR USED AS THE BASIS FOR THE MANUFACTURE OR SELL OF APPARATUS OR DEVICES WITHOUT PERMISSION.

DIMENSIONAL TOLERANCES () HOLES : ± 0.05 ANGLES : $\pm 0.5^\circ$

<30	: ± 0.25	DECIMALS	UP-100 : ± 0.2	250-300 : ± 0.4	UP-600 : ± 1.5
>30-100	: ± 0.35	X	100-150 : ± 0.25	300-350 : ± 0.45	600-900 : ± 2.4
>100-300	: ± 0.5	X,X	150-200 : ± 0.3	350-400 : ± 0.5	900-OVER : ± 3.1
ABOVE 300	: ± 0.8	X,XX	200-250 : ± 0.35		

SCALE: UNIT: mm USED ON: Planetary Gearhead

Drawn:	Design:
Description: Planetary Gearhead Servo Box	
Part No.	REV.
A3	X0
SIZE	
SHEET OF	ISSUE DATE: