



NOTES.

1. Match Motor Flange:  $\phi 80$
2. Output shaft have keyway, without keyway is optional.
3. Bushing is supplied to input bore  $\phi 10, \phi 12, \phi 12.7$  or  $\phi 14$

MODEL	段數 (Stage)	減速比 (Ratio)	背隙 (Arcmin)	匹配馬達出軸直徑&長度
PA090-C0038C1635	單段	3	8	16 & 35
PA090-C0048C1635	單段	4	8	16 & 35
PA090-C0058C1635	單段	5	8	16 & 35
PA090-C0078C1635	單段	7	8	16 & 35
PA0-90C0108C1635	單段	10	8	16 & 35

Ration Application	3,4,5,7,10
Power Application	100W ~ 400W

**DELTA** 台達電子工業股份有限公司  
DELTA ELECTRONICS, INC.

THESE DRAWINGS AND SPECIFICATIONS ARE THE PROPERTY OF DELTA ELECTRONICS, INC. AND SHALL NOT BE REPRODUCED OR USED AS THE BASIS FOR THE MANUFACTURE OR SELL OF APPARATUSES OR DEVICES WITHOUT PERMISSION.

THIRD ANGLE PROJECTION

DESCRIPTION: **Planetary Gearhead Servo Box**

PART NO. \_\_\_\_\_ REV. **X0**

SCALE \_\_\_\_\_ UNIT **mm** USED ON **Planetary Gearhead**

SHEET \_\_\_\_\_ OF \_\_\_\_\_ ISSUE DATE: \_\_\_\_\_